

In-House Paging Systems cc

Pro-Call In-House Radio Paging Systems
Herald Waiters' Silent Call Systems

Founded as *Pro-Sekure* in 1984
Member of the HBA Group of Companies
Member C Brinkworth
Company Number 2001/024306/23
VAT Number 4490197219



Phone 012 660 1100
RSA Toll-free 0800 112 868
Fax 012 660 2319
e-mail info@ihps.co.za
Website www.ihps.co.za

The On-site Calling Experts!

Ground Floor P O Box 153
CB Centre East Irene
75 Durham Road 0062
Clubview, 0014 South Africa
Centurion

Reference : G:\pros\products\compupage\Compu_Page_V132_Administrators_Guide_20080722.doc
www.pro-call.co.za/downloads/technical/compupage_administrators_guide.pdf

Administrator's Guide

Pro-Call Local-Page In-House Paging System

Administration of the *Compu-Page* software application

**These notes apply to Compu-Page Version 1.32 and higher unless otherwise noted.
Micro-Soft Windows 98 or higher is required on every PC that is to run the application.**

Usage has also been improved by the following;

The CompuPage application has been enhanced, including;

- **Facilities** may be assigned a default value for all users by the IT Manager and thereafter altered per user by logging in to CompuPage as Administrator, then selecting "Tools", "Options" and "Facilities". Thus, individual users may be assigned access to alter messages, personnel names, etc.
- **Main screen** has been improved;
 - Names are easier to read – first and second name column positions are fixed.
 - Description column is fixed in position.
 - Display sort order buttons "Pager", "Name" and "Description" buttons have been added at top of display.
 - Pager number column and details now stay aligned. (Bug fixed.)
 - Pager number may be entered directly into the box (below "Pager Details") to send a page.
 - Pager Details, Send Message, and Message Log sections of screen may now be individually re-sized.
 - Screen sizes are now saved and restored when re-opening application. (Bug fixed.)

Known bugs in Version 1.32

The database status and version display (on bottom line of screen) is not always displayed if Message Log screen is set to minimum size. A workaround is to make the Message Log screen larger, then, close CompuPage, and re-open.

"Quick-Start Installation" onto a new PC.

1. Create a shortcut to CPage.exe (which is on the central server) on the desktop of the PC.
2. Run CpReg.exe (which is in the same program folder holding the CPage.exe application).
 - 2.1. Login as "Administrator" with password "456789".
 - If this is the first time this version of software is being installed onto this PC, "Read from File", and alter the Terminal Name to the location's or user's name.
 - If this is a re-installation of this version of software onto this PC, "Read from Registry", and if necessary, make alterations as required.
 - 2.2. Write Settings to Registry
 - 2.3. Close CpReg.exe.
3. Test the system.

Since 1984 *Pro-Sekure* has supplied on-site radio paging equipment to the hospitality trade, hospitals, and to commerce and industry in Africa, the Indian Ocean Islands, and to shipping. Our products are fully backed by our own design and support team.